10/580208

## Techniques for determining glucose levels

5   ## Technical Field

The invention relates devices for the deter-
mination of glucose, to methods for calibrating or oper-
ating such devices and to methods for measuring glucose.

10

## Background Art

It has been known that the glucose of living
15  tissue can be measured non-invasively by applying a sen-
sor arrangement, in particular an electrode arrangement
to the skin of a patient and measuring the response of
the electrode arrangement to a suitable electric signal.
Such a technique is described in WO 02/069791, the dis-
20  closure of which is enclosed herein in its entirety.

Even though this type of device is well able
to monitor glucose, it needs careful calibration accord-
ing to a well-defined protocol and must be operated under
defined conditions in order to yield results of high ac-
25  curacy.

One important purpose of these devices is to
provide a prediction of the time when a patient's glucose
level may exceed certain limits. In particular, an early
prediction of a possible hypoglycemia or hyperglycemia is
30  desirable such that a patient or accompanying person may
take adequate steps to prevent such a state.

## Disclosure of the Invention

35

Hence, in a first aspect, it is an object of
the invention to provide a device and method of the type

mentioned above that allow a more accurate measurement of
the glucose level in a living body.

This object is achieved by the device and
method of claims 1 and 26.

5        According to this aspect of the invention, at
least two temperatures are measured, wherein the first
temperature depends in different manner on the skin tem-
perature of the body and on the environmental temperature
than the second temperature when the device is mounted on
10   the body in its position of operation. This allows to
compensate for the influence of both, the skin tempera-
ture and the environmental temperature, which has been
found to be advantagous because, as discussed in the de-
tailed description, both temperatures affect the signals
15   measured with the sensor arrangement in different man-
ners.

In a second aspect, the object of the first
aspect is achieved by improving the calibration of the
device. Two different calibration mechanisms are sug-
20   gested, which can be used alternatively or in combina-
tion.

In both these mechanisms, the device is as-
sumed to calculate, in normal operation, the glucose
level from a function of the type $F(s_1, s_2, \ldots s_N, a_0, a_1, \ldots a_M)$, where $F$ depends on input values $s_1 \ldots s_N$
and calibration parameters $a_0 \ldots a_M$.

In a calibration phase, series of reference
values $g(t_i)$ are obtained at times $t_i$, e.g. using conven-
tional glucose measurements. In the same phase, a series
30   of raw input values $s_j(t'_i)$ are measured at times $t'_i$,
which generally do not necessarily coincide with the
times $t_i$. At least part of the parameters $a_0 \ldots a_M$ are
then derived from these measurements by comparing the
values obtained by function $F$ against the reference val-
35   ues or against values derived from the reference values.

In most cases, the number of times the input
values $s(t'_i)$ have been measured will be considerably

larger than the number of reference values $g(t_i)$. Hence, in the first mechanism, in order to fully exploit all data, a prediction (interpolation) of the glucose level $g$ at the times $t'_i$ is calculated from the reference values

5  $g(t_i)$. Then the deviation of the values calculated by function F for the input values $s_j(t'_i)$ and the predicted glucose levels at times $t'_j$ is minimized by varying the parameters $a_0 \ldots a_M$, thereby obtaining a set of cali-brated parameters.

10       In the second mechanism, a "shift correction" is carried out during the calibration phase. For this purpose, the times $\tau_i$ are detected at which the device has shifted or moved in relation to the body during cali-bration. Such shifts generally cause the measured signals

15  to change. When comparing the values obtained by function F against the reference values or against values derived from the reference values as mentioned above, at least one parameter $a_0$ is replaced by a sum

$$\sum_{i=0}^{P} a_{0i} \cdot b_i(t)$$

20

with $b_i(t)$ being 1 (or, equivalently, any other non-zero constant value) for $\tau_i < t < \tau_{i+1}$ and 0 otherwise. As ex-plained in the detailed description, this allows to com-pensate for the effects of the shifts.

25       In any case it may be advantageous to carry out a recalibration step, e.g. each time after putting on the device. In this step, one of the parameters is re-calibrated to find an optimum agreement between the glu-cose level calculated from the function F and a glucose

30  level from a reference measurement. The reference meas-urement can e.g. be a conventional measurement, such as an invasive measurement. This allows to compensate for an offset caused by removing and remounting the device.

        In another aspect, an object of the invention

35  is to provide a device and method that are capable to provide early and reliable prediction of a possible hy-

per-. or hypoglycemia. This object is achieved by the de-
vice and method of claims 16 and 37.

The various aspects and mechanisms can be
used in combination or separately.

5


## Brief Description of the Drawings


The invention will be better understood and
objects other than those set forth above will become ap-
parent when consideration is given to the following de-
tailed description thereof. Such description makes refer-
ence to the annexed drawings, wherein:

Fig. 1 is a cross section of a device for
measuring a glucose level,

Fig. 2 is a block circuit diagram of the de-
vice of Fig. 1,

Fig. 3 is an apparatus for calibrating the
device,

Fig. 4 illustrates an advantageous aspect of
the calibration method,

Fig. 5 shows a signal shift upon a displace-
ment of the device, and

Fig. 6 illustrates a worst-case prediction of
glucose levels with and without limits for the second or-
der derivative.


## Modes for Carrying Out the Invention

30

The device:

Fig. 1 shows a cross section of a device 100
for measuring a patient's glucose level. It comprises a
housing 1 closed on one side by an electrode plate 2. A
display 3 is arranged opposite electrode plate 2. Elec-
tronic circuitry is arranged between electrode plate 2
and display 3.

Electrode plate 2 comprises an electrically
insulating substrate 4. A strip electrode 5 covered by an
insulating layer 5a and a ring electrode 6 are arranged
on an outer side 7 of insulating substrate 4. An inner
5    side 8 of insulating substrate 4 is covered by a ground
electrode 9. A plurality of though-contacts 10 connect
ring electrode 6 to ground electrode 9. A further
through-contact 11 connects one end of strip electrode 5
to a contact pad 12 arranged on inner side 8.
10                A first temperature sensor 15 is mounted to
ground electrode 9 in direct thermal contact thereto. The
large number of through-contacts 10 ensures that ground
electrode 9 follows the temperature of ring electrode 6
and therefore the temperature of the specimen, the sur-
15   face of which is indicated by a dotted line 16, closely.
                Leads 18 are provided to connect ground elec-
trode 9, contact pad 12 and first temperature sensor 15
to the electronic circuitry arranged on a printed circuit
board 19 forming an assembly of electronic components.
20   Printed circuit board 19 is advantageously arranged on a
side of the device that is substantially opposite to the
side of electrode plate 2. A battery 21 for powering the
circuitry is arranged between printed circuit board 19
and electrode plate 2.
25                A second temperature sensor 22 is arranged on
printed circuit board 19 and in direct thermal contact
thereto.
                The design of the electrodes 5, 6, 9 of the
present sensor can correspond to the one described in
30   reference to Figs. 2 and 4 of WO 02/069791, which de-
scription is enclosed by reference herein.
                Fig. 2 shows a block circuit diagram of the
circuitry of device 100. It comprises a voltage con-
trolled oscillator (VCO) 31 as a signal source for gener-
35   ating a sine wave signal or another periodic signal. This
signal is fed to two amplifiers 32, 33. The output of
first amplifier 32 is connected via a resistor R1 to a

6

first signal path 34. A resonant circuit 35 comprising an
inductance L and a capacitor C in series is connected be-
tween first signal path 34 and ground. The output of sec-
ond amplifier 33 is connected via a resistor R2 to a sec-
5  ond signal path 36. Second signal path 36 can be substan-
tially identical to first signal path 34 but comprises a
resistor R3 as a reference load instead of resonant cir-
cuit 35.

        Both signal paths 34, 36 are fed to a measur-
10 ing circuit 37, which determines the relative amplitude A
of both signals and/or their mutual phase shift phi.
Relative amplitude A can e.g. be the amplitude of first
signal path 34 in units of the amplitude of second signal
path 36 (wherein the amplitudes are the peak values of
15 the sine waves).

        The output signal of measuring circuit 37 is
fed to a microprocessor 38, which also controls the op-
eration of VCO 31.

        Microprocessor 38 further samples the first
20 and second temperature signals T1, T2 from first and sec-
ond temperature sensors 15, 22. It also controls display
device 3, an input device 40 with user operable controls,
and an interface 41 to an external computer. A memory 42
is provided for storing calibration parameters, measure-
25 ment results, further data as well as firmware for micro-
processor 38. At least part of memory 42 is non-volatile.

        Inductance L of the device of Fig. 2 can be
generated by a coil and/or by the leads and electrodes of
capacitor C. Its value is generally known with reasonable
30 accuracy.

        Capacitor C of the device of Fig. 2 is formed
between strip electrode 5 and ring electrode 6 and is
used for probing the specimen. For this purpose, the
electrodes are arranged on the skin 16 of the patient as
35 shown in Fig. 1.

        For a good and permanent contact with the pa-
tient's skin, the device is advantageously worn on an arm

or leg and provided with a suitable holder or wrist band
43.

       The geometry of the electrodes is selected
such that the electric field generated by them extends
5    into the specimen and the body liquid to be measured. Ad-
vantageously, at least one of the electrodes of the ca-
pacitor is electrically insulated such that capacitor C
is primarily a capacitive load, the capacitance and loss
of which depend on the electrical properties (i.e. the
10   response) of the specimen at the frequency of VCO 1.

       In summary, the device shown in Figs. 1 and 2
comprises:

       - an electrode arrangement or sensor arrange-
ment comprising the electrodes 5 and 6 and
15          - processing circuitry including the elements
31 - 33, 37, 38 for measuring the response of the sensor
arrangement or electrode arrangement to an electrical
signal and deriving the glucose level therefrom.

       In addition, it can comprise at least two
20   temperature sensors 15, 22, the signals of which depend
in different manner on the skin temperature of the body
and on the environmental temperature. Both these tempera-
tures can be taken into account when determining the glu-
cose level.

25

       Basic principle of operation:
       The basic principle of operation of the de-
vice is described in WO 02/069791.
       To measure the concentration of glucose in
30   the body fluid of the patient, microprocessor 38 can e.g.
initiate a measurement cycle consisting of a frequency
sweep of VCO 1. The sweep should start at a frequency
$f_{max}$ above the expected resonance frequency f0 of the
resonant circuit 5 and extend to a frequency $f_{min}$ below
35   resonance frequency f0 (or vice versa). Typical frequen-
cies are given in WO 02/069791. During this sweep, the
electrical properties of the two signal paths 34, 36 will

vary in different manner. The amplitude determined by measuring circuit A will fall to a minimum A0 at a characteristic frequency f0, as described in WO 02/069791. At the same time or close thereto, phase shift phi crosses

5    zero.

Microprocessor 38 measures A0 and/or f0 as input values describing the physiological state of the patient's tissue. In addition to the input values of A0 and/or f0, microprocessor 38 measures the temperature

10   values T1 and T2 as further input values. Using suitable calibration data, the glucose level can be derived from these input values.

Such calibration data can be determined in straightforward manner using methods known to the person

15   skilled in the art. In the following, however, some advantageous techniques are presented for the determination of the glucose level with the type of device described here as well as for its calibration.

In general, microprocessor 38 will use a formula

20   mula of the type

$$g = F(s_1, s_2, \ldots s_N, a_0, a_1, \ldots a_M) \qquad (1)$$

for determining the glucose level g (or a parameter in-

25   dicative thereof) from N measured input values $s_1$, $s_2$, $\ldots s_N$ (N > 0), where the function F has M+1 parameters $a_0$, $a_1$, $\ldots a_M$ (M ≥ 0), at least some of which have to be determined in suitable calibration experiments.

The measured input values $s_i$ are e.g. values

30   directly or indirectly derived from the amplitude A0, the corresponding frequency f0, and the temperatures T1, T2. The input values can e.g. be the most recent values measured or they can be a time average or a median over a given number of recent measurements.

35   In an advantageous embodiment, the values $s_1$ = A0, $s_2$ = f0, $s_3$ = T1 and $s_4$ = T2 are used.

The function F can be empirical or it can be based at least partially on a model describing the physical nature of the mechanisms involved.

Under the approximation that the relation between the glucose level g and the measured values $s_i$ is linear, we have

$$g = a_0 + a_1 \cdot s_1 + a_2 \cdot s_2 + \dots a_N \cdot s_N \qquad (2a)$$

with $M = N$.

Equation (2a) has the advantage of being linear in the input values $s_i$ as well as the parameters $a_j$, which simplifies calibration as well as evaluation. More refined models can, however, be used as well.

Temperature compensation:

It is presently understood that electrical properties of the topmost skin layers and therefore of the signals A0 and f0 depend not only on the glucose level, but also on the temperature Ts of the skin and underlying tissue as well as on the temperature Te of the environment. This is at least in part due to the fact these properties depend on the amount of blood in the skin and underlying tissue, which in turn affects the temperature of the skin. Hence, it is advantageous to measure the skin temperature, a first approximation of which can be derived from the signal from temperature sensor T1.

However, the skin temperature is not only a function of the amount of blood in the skin and underlying tissue, but also of the environmental temperature Te. Hence, it is also advantageous to measure the environmental temperature, a first approximation of which can be derived from the signal from temperature sensor T2.

Hence, device 100 is advantageously equipped with at least two temperature sensors T1 and T2, the signals of which depend in different manner on the temperatures Ts and Te, such that a measurement of T1 and T2 is

indicative of both temperatures Ts and Te. Hence, at
least one of the input values $s_i$ should be derived from
the signal of first temperature sensor 15 and at least
another one of the input values $s_i$ should be derived from
5   the signals of second temperature sensor 22.

        Advantageously, one of the temperature sen-
sors is closer to the electrodes 5, 6 (and therefore to
the body of the patient) than the other sensor. For exam-
ple, the first temperature sensor 15 is arranged at the
10  same side of housing 1 as the electrodes 5, 6 and the
second temperature sensor 22 at the opposite side.

        The measured values may also depend on the
temperature of the electronic circuits because the prop-
erties of voltage sources, A/D-converters and other cir-
15  cuitry are generally temperature dependent. Hence, it may
also be advantageous to measure a temperature that is in-
dicative of the circuit temperature Tc. In the present
embodiment, this is especially true for temperature T2,
i.e. by using the signal from second temperature sensor
20  22, changes of the circuit temperature Tc can be ac-
counted for. However, an additional third temperature
sensor for specifically measuring circuit temperature Tc
may be provided as well.


25        Calibration:

        In the following, advantageous methods for
calibrating the device are described.


        *a) Parameter Determination:*
30        A basic calibration of the device is required
for each new patient.

        In a first step of the basic calibration, the
patient undergoes a calibration phase in which the glu-
cose level is measured repetitively by an alternative
35  method of measurement, e.g. by a conventional invasive
technique, in order to obtain a series of K reference
values $g(t_1)$, $g(t_2)$, ... $g(t_K)$ at times $t_1$ through $t_K$. In

the same period, the input values $s_i$ are measured repetitively at L times $t'_1$ through $t'_L$, wherein L can be much larger than K. All measured values $s_i(t'_j)$ (i = 1 ... N, j = 1 ... L) are stored, e.g. in memory 42 of the device.

5        In order to derive accurate and meaningful parameters over a wide range of measurement conditions, the blood glucose level g as well as the environment temperature Te is varied during the calibration phase. For example, the environment temperature is varied over at

10   least 5 °C, preferably at least 10 °C, e.g. by carrying out indoors and outdoors measurements, and the glucose level is varied by at least 100 mg/dl, e.g. by the patient having a snack and by delaying and/or reducing insulin.

15        The calibration phase can e.g. extend over two days and include at least 10 reference values per day. Several reference values should be recorded in the periods during which the glucose level and/or temperature are varied as described above in order to obtain a full

20   record of these events.

        Alternatively to or in addition to an intensive calibration phase of two days, an extensive calibration can be carried out during a period of e.g. 15 days that allows the device to "adapt" to a given user. During

25   this extensive calibration phase, reference measurements will again be carried out, e.g. invasively, even though at less frequent intervals.

        The data recorded during the calibration phase can be used for finding appropriate values for at

30   least part of the parameters $a_i$. For this purpose, the values obtained by function F according to equation (1) are compared against the reference values $g(t_i)$ or against values derived therefrom, and those parameters $a_i$ are determined for which this comparison gives a closest

35   match.

        In a most simple approach, the parameters $a_i$ can be obtained from a conventional least-squares fitting

algorithm. Suitable algorithms are known to a person
skilled in the art and are e.g. described by Press, Teu-
kolsky, Vetterling and Flannery in "Numerical Recipes in
C", Cambridge University Press, $2^{nd}$ edition, 1992, Chapter
15. For evaluating the function F at the times $t_1$ through
$t_k$, only the input values $s_i$ at the times closest to $t_1$
through $t_k$ are required.

This simple approach, however, will only ex-
ploit part of the available information. In particular,
it ignores the information obtained by the measurements
of the input values $s_i(t'_j)$ at times $t'_j$ other than the
times $t_1$ through $t_k$.

In an advanced approach, the reference values
$g(t_i)$ are used to calculate a prediction (interpolation)
of the actual glucose levels at times between the meas-
urement times $t_1, \ldots t_k$, in particular at all times $t'_1$
$\ldots t'_L$. Then, the deviation of this prediction from the
value of function F for the corresponding input values $s_i$
is calculated and the total deviation is minimized by
varying the parameters $a_i$.

An empirical, semi-empirical or theoretical
model of the variation of the glucose level in a body can
be used for calculating the prediction (interpolation).

An advantageous model is based on the under-
standing that the rate of change of the glucose level is
limited. For human beings, a typical maximum rate of in-
crease is $\dot{g}_{incr} = 3.5$ mg·dl$^{-1}$·min$^{-1}$ and a typical maximum
rate of decrease is $\dot{g}_{decr} = 4$ mg·dl$^{-1}$·min$^{-1}$ as well. This
allows to predict a set S of possible glucose values for
any time t between the times $t_1$ through $t_K$ as depicted in
Fig. 4. S is the set of values delimited by lines of
slope $\dot{g}_{incr}$ and $\dot{g}_{decr}$ extending from the measured points
$g(t_i)$.

Taking this model into account, a possible
calibration procedure is based on the following steps:
  - Step 1: The patient undergoes the calibration phase
    as mentioned above in which the K reference values

g($t_i$) and the L×N input values $s_j(t'_i)$ are measured and recorded.

- Step 2: Equation (1) is fitted to the measured reference values g($t_1$) ... g($t_K$) by evaluating

$$f_i = F(s_1(t_i) \ ... \ s_N(t_i), a_0 \ ... \ a_M) \qquad (3)$$

at each time $t_i$ and comparing $f_i$ to g($t_i$). If the input values $s_j(t_i)$ at time $t_i$ are not known (because none of the $t'_k$ matches $t_i$ exactly, an estimate of the values $s_j(t_i)$ from measured input values $s_j(t'_k)$ for at least one $t'_k$ close to $t_i$ can be used. Then the parameters $a_1$ ... $a_M$ are varied to find a set of parameters where the total deviation between the values $f_i$ and g($t_i$) is at a minimum, e.g. by minimizing the sum of the squares of all $f_i$. This basic fitting process provides a set of starting values for the parameters $a_i$ in the following step 3.

- Step 3: The deviation of

$$F(t'_i) = F(s_1(t'_i) \ ... \ s_N(t'_i), a_0 \ ... \ a_M) \qquad (4)$$

for all times $t'_i$ from the prediction S at the corresponding times $t'_i$ is minimized by varying the parameters $a_i$. This can e.g. be achieved by defining, for each time $t'_i$, a predicted distribution S($t'_i$) of the glucose value and by calculating a deviation $d_i$ by comparing the predicted distribution S($t'_i$) with the value F($t'_i$). In the model of Fig. 4, a suitable deviation $d_i$ can e.g. be defined as

$$d_i = \begin{cases} F(t'_i) - S_{max}(t'_i) & \text{if } F(t'_i) > S_{max}(t'_i) \\ S_{max}(t'_i) - F(t'_i) & \text{if } F(t'_i) < S_{min}(t'_i) \\ 0 \text{ otherwise} \end{cases} \qquad (5)$$

with $S_{min}(t'_i)$ and $S_{max}(t'_i)$ being the range of the set S of Fig. 4 at time $t'_i$, i.e.

$$S_{max}(t'_i) = \min(g(t_j) + \dot{g}_{incr} \cdot (t'_i - t_j),$$
$$g(t_{j+1}) + \dot{g}_{decr} \cdot (t_{j+1} - t'_i)) \quad (6a)$$

and

$$S_{min}(t'_i) = \max(g(t_j) - \dot{g}_{decr} \cdot (t'_i - t_j),$$
$$g(t_{j+1}) - \dot{g}_{incr} \cdot (t_{j+1} - t'_i)) \quad (6b)$$

where $t_j$ is the closest of the times $t_1 \ldots t_K$ prior to $t'_i$.

The parameters $a_1 \ldots a_M$ can then e.g. be found by minimizing the value

$$D = \sum d_i \quad (7)$$

numerically. Corresponding techniques are known to the person skilled in the art and e.g. described in Chapter 10 of the book "Numerical Recipes in C" cited above.

It must be noted that step 2 is optional if the starting values of step 3 are obtained by some different method, e.g. from typical values, or if step 3 uses an algorithm that does not require starting values for the parameters. Alternatively, step 3 can be omitted if the results from step 2 are to be used directly.

It must further be noted that equations (5) through (7) are advantageous examples but can be replaced by other suited definitions.

For example, instead of using a prediction S that gives a simple range, a prediction providing a probability density $S(g, t'_i)$ can be used, indicating the probability to observe a given glucose value g at time $t'_i$. Such a probability can e.g. be derived from an empirical or semi-empirical model that predicts how prob-

able a given value of the glucose level is at time $t'_i$, given the reference values $g(t_j)$. Apart from the reference values, a suitable model can e.g. take the physiological parameters of the patient (e.g. body weight) as

5  well as events during the calibration phase (e.g. food intake, insulin administration etc.) into account for improving the accuracy of the prediction.

Equation (7) can also be replaced by any other suitable measure for the deviation of the function

10  F from the prediction S. In particular if the probability of a certain deviation $d_i$ is known, the formula for D should be defined in such a manner that its minimum coincides with the set of parameters having the highest statistical probability. For details, we refer to the book

15  "Numerical Recipes in C" cited above.

Calibration is preferably carried out with a system as shown in Fig. 3, where an external computer 102 can be connected to the device 100 through interface 41. Computer 102 can instruct device 100 to start a calibra-

20  tion process, whereupon device 100 can be disconnected from the computer and be applied to the patient for carrying out above step 1. Then the reference values $g(t_i)$ are entered into computer 102, and the measured input values $s_j(t'_i)$ are transferred to computer 102 via inter-

25  face 41. Above steps 2 and 3 are carried out in computer 102 and the resulting parameters $a_i$ are transferred back to device 100, which, after a final test of the performance of the calculated parameters $a_i$, is then ready for regular operation.

30      Even though the capabilities of computer 102 may be integrated directly into device 100, it is generally advantageous to use a separate computer system for the convenience of its use and its computational power.

35      b) *Shift correction during calibration:*
During the above basic calibration, movements of the patient or other events may cause device 100 to

change its position in respect to the patient's body. Displacements of this type will usually lead to a change in signal that should be accounted for.

For taking such shifts into account, it is advantageous to introduce additional auxiliary parameters $a_{00}$, $a_{01}$, ... $a_{0P}$ during the above calibration steps. Assuming that $a_0$ is a purely additive parameter in function F (such as in the example of equation (2)), equations (3) and (4) above are replaced by

$$f_i = F(s_1(t_i) \ldots s_N(t_i), 0, a_1 \ldots a_M) + a_{00} \cdot b_0(t_i) + \ldots + a_{0P} \cdot b_P(t_i) \qquad (3')$$

and

$$F(t'_i) = F(s_1(t'_i) \ldots s_N(t'_i), 0, a_1 \ldots a_M) + a_{00} \cdot b_0(t'_i) + \ldots + a_{0P} \cdot b_P(t'_i), \qquad (4')$$

where the functions $b_i(t)$ are 0 unless the time t is in the range $\tau_i \ldots \tau_{i+1}$, where they are 1.

In other words, the additive parameter $a_0$ of function F is set to 0 (or, equivalently, another fixed value), and it is replaced by parameter $a_{00}$ in time interval $\tau_0 \ldots \tau_1$, by parameter $a_{01}$ in time interval $\tau_1 \ldots \tau_2$, etc.

The times $\tau_0$ and $\tau_P$ are the start and end times of the calibration phase and the other times $\tau_i$ are the times when a "shift" of device 100 is detected during the calibration phase. Such a shift can e.g. be detected because at least one of the input values $s_i$ (such as the amplitude $A_0$ or frequency $f_0$) changes by more than a given threshold value $\Delta s_i$ during two consecutive measurements. Details on how to detect such "shifts" are discussed in the section "shift correction during measurements" below.

By using equations (3') and (4') instead of (3) and (4), the parameters $a_{00} \ldots a_{0P}$ and $a_1 \ldots a_M$ can

be determined using steps 2 and 3 described in the previous section. The parameters $a_1 \ldots a_M$ can then be used during normal operation of the device.

As to additive parameter $a_0$, that parameter can be roughly approximated to be the median or average of parameters $a_{00} \ldots a_{0P}$, but it is preferably determined from later recalibration measurements as described in section "Recalibration" below.

Instead of using additive parameters $a_{00} \ldots a_{0P}$, multiplicative parameters might be used for this kind of correction as well. In that case, equations (3') and (4') should be changed accordingly.

In more general terms, a compensation of "shifts" or displacements of device 100 during calibration can be achieved by replacing at least one of the parameters, e.g. $a_0$, in equations (3) and (4) by

$$\sum_{i=0}^{P} a_{0i} \cdot b_i(t), \tag{8}$$

with $b_i(t)$ being 1 for $\tau_i < t < \tau_{i+1}$ and 0 otherwise. The parameters to be replaced in this way are those parameters that are most sensitive to shifts of the device.

In most cases, it will be sufficient to apply this technique to the one additive or one multiplicative parameter in F. (Definition: A parameter $a$ is additive if function $f(a, \ldots)$ can be re-written as $a + f'(\ldots)$ with $f'$ being independent of $a$; a parameter $a$ is multiplicative if function $f(a, \ldots)$ can be re-written as $a \cdot f''(\ldots)$ with $f''$ being independent of $a$).


Normal operation:

After calibration of the device, all or at least most of the parameters $a_0 \ldots a_M$ are known. In a very simple device, such as described in WO 02/069791, all parameters can be determined completely during calibration and then equation (1) can be used for determining the glucose level from the measured input values $s_i(t)$ in regular operation.

In the following, however, some additional steps are described that allow to improve the accuracy of the device.

5      *a) Recalibration*

After the calibration steps described above, all parameters $a_i$ are known if it is assumed that no shift correction is necessary, i.e. if it is assumed that the device is being held at a fixed position on the pa-
10    tient's body.

If a shift of the device against the body is to be compensated for, at least one parameter, such as the additive or multiplicative parameter $a_0$, can only be determined inaccurately during calibration because the
15    device may have been displaced during calibration or between calibration and regular measurement. In that case it is advantageous to carry out recalibration measurements during regular operation, e.g. once a day after affixing the device to the body.

20    A recalibration measurement consists, in a simple embodiment, of a single measurement of the glucose level $g(t_0)$ by conventional means. This glucose level is then entered into device 100 with a command to carry out recalibration.

25    When ordered to carry out a recalibration, microprocessor 38 finds the solution or optimum agreement of

$$g(t_0) = F(s_1(t_0) \ldots s_N(t_0), a_0, a_1, \ldots a_M) \quad (9)$$

30

by varying one of the parameters, usually the additive or multiplicative parameter $a_0$. The parameter found in this way is then used for following measurements.

For solving equation (9), the input values
35    $s_1(t_0) \ldots s_N(t_0)$ may be derived from a single measurement at time $t_0$ or from an average, median or interpolation value of several measurements around time $t_0$. Assum-

ing that parameters $a_1$ to $a_M$ are known, parameter $a_0$ can
then be calculated e.g. numerically by a root finding al-
gorithm as known to the person skilled in the art.

A corresponding recalibration means can e.g.
5  be implemented as a firmware program for microprocessor
38.


b) *Shift correction during normal operation*

As mentioned in the section "shift correction
10 during calibration" above, a movement or "shift" of the
device 100 in respect to the body may cause a change in
measured signals. Even if all parameters are known from
calibration or recalibration measurements as described
above, such a shift may invalidate subsequent measure-
15 ments.

To avoid this, microprocessor 38 of device
100 is advantageously programmed to detect such a shift.
For this purpose, at least one signal value $v(t)$ can be
monitored, wherein the signal value $v(t)$ is any value
20 that is derived directly or indirectly from at least one
of the input values $s_i(t)$ and that shows a characteristic
shift when device 100 is moved in respect to the pa-
tient's body.

In particular, the signal value $v(t)$ can be
25 one of the following:
   - One of the input values $s_i(t)$; for example, fre-
     quency $f_0$ or amplitude $A_0$ can be used since both
     these values show a change when device 100 is
     moved.
30 - The glucose value g derived from function F in
     equation (1). This value also shows a change when
     the device is moved.
   - Any intermediate result generated during the
     evaluation of function F that shows a easily de-
35     tected change when device 100 is moved.

Fig. 5 shows a typical shift of signal value
.v(t) when device 100 is displaced along the patient's

body at a time ts. As can be seen, prior and after the
event, the signal value is fairly continuous (e.g. linear) while there is a sudden change between the measurements before and after time ts.

To detect a shift of this type, the following
three steps are carried out at a given time t:

- Step 0: Calculate an extrapolated signal value
  $v_{ext}(t)$ as an extrapolation from a number of previous signal values v. Advantageously, $v_{ext}(t)$ is
  calculated only from signal values v older than t
  − $\Delta t$. $\Delta t$ is a window length, which can e.g. be 5
  minutes if one measurement is carried out each
  minute.

- Step 1: Determine an actual signal value $v_{act}(t)$
  from one or more current signal values v. Advantageously, $v_{act}(t)$ is calculated from a median or
  average of the signal values within the time window t − $\Delta t$ and t.

- Step 2: Compare the actual signal value $v_{act}(t)$
  to the extrapolated signal value $v_{ext}(t)$ and assume that a "shift" has occurred if the values
  differ by a given threshold amount. This threshold should be larger than a typical noise-induced
  variation between consecutive signals and is e.g.
  in the order of 5% of a typical value of v(t) if
  v(t) = $f_0(t)$ is used. If the change exceeds the
  threshold amount, a shift correction procedure is
  started.

The shift correction procedure includes the following
steps:

- Step 3: Define the exact time $t_s$ of the shift.
  This can e.g. be done by iterating over a given
  number of recent signal values v(t), e.g. the
  values in the above time window t − $\Delta t$ and t, and
  looking for the largest change of consecutive
  values $v(t_i)$ and $v(t_{i-1})$.

- Step 4: Derive a shift correction $\Delta v$ from an extrapolation of older values (e.g. the extrapolation $v_{ext}(t)$ mentioned above) and from values measured after the time $t_S$ of the shift. For example, the difference or ratio between
  - the median or average of the signal values in interval $t_S \dots t$ and
  - the extrapolation $v_{ext}(t)$

can be calculated and be used as shift correction $\Delta v$. If the difference is used, the shift correction will be an additive correction to be added to $v$, otherwise it will be multiplicative correction to be multiplied to value $v$.

- Step 5: Use the shift correction for correcting subsequently measured glucose values. The specific implementation of this step depends on the definition of the signal value $v(t)$. Examples:
  - If signal value $v(t)$ is equal to an input value $s_i(t)$, such as $f_0(t)$ or $A_0(t)$, subsequently measured input values should be corrected by $s_i(t) + \Delta v$ (additive correction) or by $s_i(t) \cdot \Delta v$ (multiplicative correction) before inserting them into function F for evaluation.
  - If signal value $v(t)$ is equal to the glucose value $g(t)$ evaluated from function F, $\Delta v$ can be added to or multiplied with the returned function value. Alternatively, if F has an additive or multiplicative parameter $a_0$, that parameter can be corrected by addition of or multiplication with $\Delta v$.

Corrections for other types of signal values $v(t)$ can also be implemented by correcting the input values, parameters, intermediate results or return value of function F in order to make sure that function F returns the same results before and after time $t_S$.

Above steps 0 to 5 can be implemented in a
shift correction by suitable firmware in microprocessor
38 of device 100. In general, the shift correction should
be able to

5              - detect a displacement of device 100 along the
                 body of the patient, e.g. based on steps 0 to 2
                 above or any other method that is able to deter-
                 mine a sudden shift in a signal value,
               - determine an effect of the shift on the measured
10               glucose level, e.g. based on step 4 above, and
               - correct the measured glucose levels after the
                 shift to compensate for the determined effect.
        It must be noted that the signal value used
in steps 0 to 3 does not need to be the same as the one
15  used in steps 4 and 5. It may be advantageous to use a
raw input signal, such as $f_0$ and $A_0$ for sensitively de-
tecting a displacement of the device in steps 0 to 3,
while it may be easier to carry out the correction on the
function's F return value or an additive or multiplica-
20  tive parameter $a_0$ in steps 4 and 5.


        Range monitoring:
        As mentioned above, an important purpose of
device 100 is to provide a prediction of the time when a
25  patient's glucose level may cross given safety limits.
        For this purpose, microprocessor 38 comprises
a software-implemented predictor that tries to predict
when, at an earliest time, the glucose level g is likely
to fall below a lower limit $g_{min}$ and/or to rise above an
30  upper limit or $g_{max}$. Typical values for $g_{min}$ are in the
order of 50 to 80 mg/dl, e.g. 70 mg/dl, and for $g_{max}$ they
are above 160 mg/dl, e.g. 250 mg/dl.
        Such predictors have been known to rely on
the maximum rate of decrease is $\dot{g}_{decr}$ mentioned above,
35  assuming that the first derivative $\dot{g}$ of the glucose
level will never fall below the maximum rate of decrease,

i.e. $\dot{g} \geq -\dot{g}_{decr}$ (if $\dot{g}_{decr}$ is defined to be a positive value).

It has been found, however, that this type of prediction can be improved. It has been found that not only the first derivative $\dot{g}$ of the glucose level is limited, but also the second derivative $\ddot{g}$. Typical lower and upper limits $\ddot{g}^-$ and $\ddot{g}^+$ were found to be both at 0.1 $mg \cdot dl^{-1} \cdot min^{-2}$.

This is illustrated in Fig. 6 showing a series of glucose level measurements g(t) indicated by dots. The lines p1 and p2 represent worst-case decay predictions starting from time t0. p1 is calculated on the mere assumption that $\dot{g} \geq -\dot{g}_{decr}$, while p2 is calculated from the refined assumption that $\dot{g} \geq -\dot{g}_{decr}$ and $\ddot{g} \geq -\ddot{g}^-$. As can be seen, the time t1 where prediction p1 reaches $g_{min}$ is smaller than the time t2 where prediction p1 reaches $g_{min}$. Hence, using prediction p2 allows to avoid unnecessary alerts and allows a more precise prediction.

To make a prediction of type p2, it is necessary to use not only the actual values g(t0) of the glucose, but also a first derivative $\dot{g}$(t0) thereof. In the example of Fig. 6, time t2 - t0 can e.g. be calculated from g(t0), $\dot{g}$(t0), $\ddot{g}^-$ and $\dot{g}_{decr}$ using simple analysis.

Instead of calculating a time t2 where a worst-case prediction g(t) is expected to reach $g_{min}$, it is also possible to make a worst-case prediction at a time t + $\Delta$t, where $\Delta$t is a fixed "safety margin" of e.g. 20 minutes, and to compare this worst-case prediction g(t + $\Delta$t) e.g. to the lower threshold value $g_{min}$. If the worst-case prediction is below the threshold value, an alert is issued.

In general, range monitoring will therefore advantageously calculate a prediction of the glucose level from an estimate of the current value of the glucose level g(t0) as well as its derivative $\dot{g}$(t0), taking into account that the prediction must fulfil the conditions $\dot{g} \geq -\dot{g}_{decr}$ and $\ddot{g} \geq -\ddot{g}^-$ and/or $\dot{g} \leq \dot{g}_{incr}$ and $\ddot{g} \leq \ddot{g}^+$

24

This type of monitoring can be used in the
device 100 but also in any other type of device that has
a detector for repetitively measuring the glucose level
of a living body. The prediction can, in particular, be
5 used to provide an alert if the worst-case time until a
hypoglycemia ($g(t) < g_{min}$) or hyperglycemia ($g(t) > g_{max}$)
is below a given threshold time.


10          Remarks:

As it will be clear to the person skilled in
the art, the methods described above can also be carried
out with devices different from the one of Figs. 1 and 2,
such as any of the devices shown in WO 02/069791 (taking
15 into account that the temperature compensation described
above will require the addition of a second temperature
sensor).

Most aspects of the present invention, such
as a temperature compensation, shift correction and vari-
20 ous calibration methods, also work with devices using
other types of sensors, such as optical sensors or induc-
tive sensors.

While there are shown and described presently
preferred embodiments of the invention, it is to be dis-
25 tinctly understood that the invention is not limited
thereto but may be otherwise variously embodied and prac-
ticed within the scope of the following claims.